

**HS014G**

AKUMULATORSKA KRUŽNA TESTERA

ADT AWS XPT**DOSTUPNO KAO**

HS014GZ bez akumulatora i punjača

POGODNOSTI ZA KORISNIKE

- Maksimalna dubina rezanja od 47 mm omogućava rezanje komada drveta debljine 45 mm u samo jednom potezu, što ovaj alat čini idealnim za drvene konstrukcije, drvene podne obloge...
- AFT tehnologija automatski prepoznaje nagli pad brzine lista testere usled povratnog udara i zaustavlja motor kako bi se smanjila posledična sila reakcije
- Električna kočnica za maksimalnu produktivnost i veću bezbednost korisnika
- AWS tehnologija putem Bluetooth veze povezuje alat sa usisivačem i automatski pokreće usisavanje kad god se alat koristi

**TEHNIČKE SPECIFIKACIJE**

Napon akumulatora	40 V max XGT
Brzina bez opterećenja	6.400 min ⁻¹
List testere/otvor Ø	125/20 mm
Maks. kapacitet rezanja na 0°	47 mm
Maks kapacitet rezanja na 45°	30 mm
Opseg nagiba	15–45°
Dimenzije (D×Š×V)	264 x 203 x 246 mm
Težina*	3,1 kg

*Sa BL4020

POSEBNOSTI PROIZVODA

Funkcija duvalice
Oduvava piljevinu kako bi se omogućio bolji pogled na liniju rezanja.



Dodatna osnova od livenog aluminijuma
Omogućava precizno paralelno podešavanje, kao i podešavanje pod pravim uglom.



Sečenje uz zid
Uklanjanjem dodatne osnove omogućava se rezanje blizu zida. Dodatna osnova se može ukloniti bez primene alata.

**BUKA I VIBRACIJE**

Nivo zvučnog pritiska: **94 dB(A)**, Nivo zvučne snage: **102 dB(A)**, Nivo vibracija: **1,0 m/s²**

**KOMPATIBILNOST**Preporučeno: **BL4020, BL4025, BL4040, BL4040F****PRIBOR**

Efficut list testere
E-28880 - 25T drvo



Adapter vodice
191L92-3



Vodice
199140-0 - 1,0 m
199141-8 - 1,5 m
194925-9 - 1,9 m
194367-7 - 3,0 m
Set za spajanje vodica 198885-7

Efficut list testere
B-69462 - 45T drvo



Komplet brzih stega
199826-6



Paralelna vodica
1918P3-6



Brza stega za vodicu
1913K5-7

**POVEZANI PROIZVODI**

40 V max XGT
HS012G
Akumulatorska kružna testera



40 V max XGT
TM001G
Akumulatorski višenamenski alat



40+40 V max XGT
VC006GM
Akumulatorski usisivač



40 V max XGT
VC004GL
Akumulatorski usisivač



40 V max XGT
SP001G
Akumulatorska testera sa uranjanjem

www.makita.rs

Grupacija Makita zadržava pravo na izmene u ovom letku, u svim oblicima i metodama povezanim sa ovim letkom. Slike mogu da se razlikuju od stvarnih proizvoda.